



>>RP-2801 1-P Print Fast Ethernet Server

RP-2801 print server equips 1*Parallel interface for users to share their printers on Intranet/Internet. The print server allows the printers placed in the convenient location and connected directly on the Ethernet network and no need to connect printer with PC.

RP-2801 supports the Simple Network Management Protocol (SNMP), which allows to remote printer management and to send warning notice. A standard SNMP agent is permanent on these print servers. Any standard SNMP-based application can be used to access and manage these print servers. The print server provides an embedded web server which can be accessed via web browser, and it also supports subsidiary Windows-based PAdmin utility which helps administrator to setup print server environment, e.g. Netware, Windows 95/98/ME/NT/2000/XP/2003, Mac or Linux system.

FEATURE

- Supports Internet Printing Protocol (IPP)
- Supports Print Job Control/Status
- Supports Email Alert
- Supports Rendezvous
- Supports DHCP Client
- Supports SNMP & HP Web JetAdmin
- Windows Print Monitor Technology
- Easy-to-use Setup Wizard

SPECIFICATION

Standards	<ul style="list-style-type: none">• IEEE802.3 10BASE-T, IEEE802.3u 100BASE-TX
Interface	<ul style="list-style-type: none">• 1 * DB-36-pin male Centronics port, supporting bi-directional• 1 * RJ-45 10/100M port
Hardware	<ul style="list-style-type: none">• ARM7-based processor• Flash: 1MB, System memory: 2MBytes SDRAM
OS Support	<ul style="list-style-type: none">• Microsoft Windows 9X/ME/NT4 (SP6)/2000 (SP4)/XP (both 32 and 64)/Vista (both 32 and 64)/7 (both 32 and 64), Apple Mac OS 8.x/9.x and 10.2 or higher, Unix/Linux, Novell NetWare 3.12 (Bindery)/4.x (both Bindery and NDS) or higher.
Protocol Support	<ul style="list-style-type: none">• IPX (Microsoft Windows Vista and 7 are exclusive), TCP/IP (LPR, IPP, RAW 9100), NetBEUI (Microsoft Windows XP, Vista, and 7 are exclusive), AppleTalk, SNMP (management), SMB.
Management	<ul style="list-style-type: none">• Web interface• Windows-based Setup Program
Default IP Address	<ul style="list-style-type: none">• 192.168.10; DHCP: off
Software Upgradeable	<ul style="list-style-type: none">• Web interface• Window-based Setup Program, TFTP
LED Indicators	<ul style="list-style-type: none">• Power/Status: Orange• LAN Link: Yellow for 10Mbps, Green for 100Mbps
Reset Button	<ul style="list-style-type: none">• Yes. (Reset, Load factory defaults, Self test page)
Power Adapter	<ul style="list-style-type: none">• External power Adapter DC3.3V, 2A
Environment	<ul style="list-style-type: none">• Operating Temperature: 0°C ~ 50°C• Operating Humidity: 0% ~ 70%
Dimension	<ul style="list-style-type: none">• 55.5 * 52 * 22 mm
Certifications	<ul style="list-style-type: none">• FCC, CE

Ordering information

RP-2801 1-P Print Fast Ethernet Server